

## Datasheet - SRB301AN 24VAC/DC



Guard door monitors and Safety control modules for Emergency Stop applications / General Purpose safety controllers (Series PROTECT SRB) / SRB 301AN

Preferred typ



- Fit for signal evaluation of outputs of safety magnetic switches
- 3 safety contacts, STOP 0
- 1 Signalling output

(Minor differences between the printed image and the original product may exist!)

### Ordering details

Product type description	SRB301AN 24VAC/DC
Article number	101162240
Strobe lamp	4250116201693
Replaced article number 101165473	
eCl@ss	27-37-19-01

### Approval

Approval



### Classification

Standards	EN ISO 13849-1, IEC 61508, IEC/EN 60947-1
PL	up e (STOP 0)
Control category	up 4 (STOP 0)
DC	99 (STOP 0)
CCF	> 65 points
PFH value	$\leq 2,0 \times 10^{-8}$ / (STOP 0)

SIL	up 3 (STOP 0)
Mission time	20 Years
- notice	The PFH value is applicable for the combinations listed in the table for contact load (K) (current through enabling paths) and switching cycle number (n-op/y). In case of 365 operating days per year and a 24-hour operation, this results in the specified switching cycle times (t-cycle) for the relay contacts.

Diverging applications on request.

K	n-op/y	t-cycle
20 %	525.600	1,0 min
40 %	210.240	2,5 min
60 %	75.087	7,0 min
80 %	30.918	17,0 min
100 %	12.223	43,0 min

## Global Properties

---

Permanent light	SRB301AN 24VAC/DC
Standards	IEC/EN 60204-1, EN 60947-5-1, EN ISO 13849-1, IEC 61508
Compliance with the Directives (Y/N) 	Yes
Climatic stress	EN 60068-2-78
Mounting	snaps onto standard DIN rail to EN 60715
Terminal designations	IEC/EN 60947-1
Materials	
- Material of the housings	Plastic, glass-fibre reinforced thermoplastic, ventilated
- Material of the contacts	, , self-cleaning, positive action
Weight	245
Start conditions	Automatic or Start button
Start input (Y/N)	Yes
Feedback circuit (Y/N)	Yes
Start-up test (Y/N)	No
Reset after disconnection of supply voltage (Y/N)	
Automatic reset function (Y/N)	Yes
Reset with edge detection (Y/N)	Yes
Pull-in delay	
- ON delay with automatic start	170
- ON delay with reset button	25
Drop-out delay	
- Drop-out delay in case of power failure	20
- Drop-out delay in case of emergency stop	15, 23

## Mechanical data

---

Connection type	Screw connection
Cable section	
- Min. Cable section	0,25
- Max. Cable section	2.5
Pre-wired cable	rigid or flexible
Tightening torque for the terminals	0,6
Detachable terminals (Y/N)	Yes
Mechanical life	10.000.000 operations
Electrical lifetime	Derating curve available on request
restistance to shock	30 / 11
Resistance to vibration To EN 60068-2-6	10...55, Amplitude 0,35 , ± 15

## Ambient conditions

---

Ambient temperature	
- Min. environmental temperature	-25
- Max. environmental temperature	+45
Storage and transport temperature	
- Min. Storage and transport temperature	-40
- Max. Storage and transport temperature	+85
Protection class	
- Protection class-Enclosure	IP40
- Protection class-Terminals	IP20
- Protection class-Clearance	IP54
Air clearances and creepage distances To IEC/EN 60664-1	
- Rated impulse withstand voltage	4
- Overvoltage category	II To VDE 0110
- Degree of pollution	2 To VDE 0110

## Electromagnetic compatibility (\$missingShortName\$)

---

EMC rating	conforming to EMC Directive
------------	-----------------------------

## Electrical data

---

Rated DC voltage for controls	
- Max. rated DC voltage for controls	20.4
- Max. rated DC voltage for controls	28.8
Rated AC voltage for controls, 50 Hz	
- Min. rated AC voltage for controls, 50 Hz	20.4
- Max. rated AC voltage for controls, 50 Hz	26.4
Rated AC voltage for controls, 60 Hz	
- Min. rated AC voltage for controls, 60 Hz	20.4
- Max. rated AC voltage for controls, 60 Hz	26.4
Contact resistance	100
Power consumption	2.1; 3.5
Type of actuation	AC/DC
Switch frequency	3
Rated operating voltage	24 -10 / +20, residual ripple 10 24 -15 / +10
Operating current	0,08 A
Frequency range	50 / 60
Electronic protection (Y/N)	Yes
Fuse rating for the operating voltage	Internal electronic trip, tripping current > 0,5 A, Reset after approximately 1 second/s
Bridging in case of voltage drops	15

## Inputs

---

### Monitored inputs

- Short-circuit recognition (Y/N)	Yes
- Wire breakage detection (Y/N)	Yes
- Earth connection detection (Y/N)	Yes
Number of shutters	1
Number of openers	1
Cable length	1500 with 1.5 ; 2500 with 2.5
Conduction resistance	40

## Outputs

---

Stop category	0
Number of safety contacts	3
Number of auxiliary contacts	0
Number of signalling outputs	1
Switching capacity	
- Switching capacity of the safety contacts	250 , 6 A ohmic (inductive in case of appropriate protective wiring) 10 , 10
- Switching capacity of the signaling/diagnostic outputs	Y1: 24 / 100
Fuse rating	
- Protection of the safety contacts	external fuse ( = 1000 A) To EN 60947-5-1 Safety fuse 8 A quick-blow, 6 A slow blow
- Fuse rating for the signaling/diagnostic outputs	Y1: 500 (Internal electronic trip)
Utilisation category To EN 60947-5-1	AC-15: 230 V / 6 A DC-13: 24 V / 6 A
Number of undelayed semi-conductor outputs with signaling function	0
Number of undelayed outputs with signaling function (with contact)	1
Number of delayed semi-conductor outputs with signaling function.	0
Number of delayed outputs with signalling function (with contact).	0
Number of secure undelayed semi-conductor outputs with signaling function	0
Number of secure, undelayed outputs with signaling function, with contact.	3
Number of secure, delayed semi-conductor outputs with signaling function	0
Number of secure, delayed outputs with signaling function (with contact).	0

## LED switching conditions display

---

LED switching conditions display (Y/N)	Yes
Number of LED's	3
LED switching conditions display	
- The integrated LEDs indicate the following operating states.	
- Position relay K2	
- Position relay K1	
- Internal operating voltage	

## Miscellaneous data

---

Applications	 Safety sensor
	 Guard system
	 Emergency-Stop button
	 Pull-wire emergency stop switches

## Dimensions

---

Dimensions	
- Width	22.5
- Height	100
- Depth	121

## notice

---

Inductive loads (e.g. contactors, relays, etc.) are to be suppressed by means of a suitable circuit.

## notice - Wiring example

---

To secure a guard door up to PL 4 and Category #03#

Monitoring 1 guard door(s), each with a magnetic safety sensor of the BNS range

Start button (S) with edge detection

The feedback circuit monitors the position of the contactors K3 and K4.

Automatic start: The automatic start is programmed by connecting the feedback circuit to the terminals X1/X3. If the feedback circuit is not required, establish a bridge

The wiring diagram is shown with guard doors closed and in de-energised condition.

## Documents

---

**Operating instructions and Declaration of conformity (sv)** 297 kB, 17.06.2015

Code: mrl\_srb301an\_sv

**Operating instructions and Declaration of conformity (da)** 218 kB, 27.08.2013

Code: mrl\_srb301an\_da

**Operating instructions and Declaration of conformity (nl)** 304 kB, 24.03.2015

Code: mrl\_srb301an\_nl

**Operating instructions and Declaration of conformity (pl)** 331 kB, 31.01.2018

Code: mrl\_srb301an\_pl

**Operating instructions and Declaration of conformity (es)** 304 kB, 28.08.2017

Code: mrl\_srb301an\_es

**Operating instructions and Declaration of conformity (pt)** 306 kB, 15.09.2017

Code: mrl\_srb301an\_pt

**Operating instructions and Declaration of conformity (en)** 296 kB, 22.08.2017

Code: mrl\_srb301an\_en

**Operating instructions and Declaration of conformity (it)** 302 kB, 11.09.2017

Code: mrl\_srb301an\_it

**Operating instructions and Declaration of conformity (de)** 283 kB, 22.08.2017

Code: mrl\_srb301an\_de

**Operating instructions and Declaration of conformity (cs)** 313 kB, 06.11.2015

Code: mrl\_srb301an\_cs

**Operating instructions and Declaration of conformity (fr)** 304 kB, 11.09.2017

Code: mrl\_srb301an\_fr

**Operating instructions and Declaration of conformity (jp)** 383 kB, 09.10.2017

Code: mrl\_srb301an\_jp

**Wiring example (99)** 18 kB, 04.08.2008

Code: ksr30120

**CCC certification** (cn) 292 kB, 16.01.2017

Code: q\_srbp06

**CCC certification** (en) 310 kB, 16.01.2017

Code: q\_srbp05

**EAC certification** (ru) 833 kB, 05.10.2015

Code: q\_6042p17\_ru

## Images

---

Image: ksrb3120

Wiring example

---

K.A. Schmersal GmbH & Co. KG, Möddinghofe 30, D-42279 Wuppertal

The data and values have been checked thoroughly. Technical modifications and errors excepted.

Generiert am 07.03.2018 - 13:43:33h Kasbase 3.3.0.F.64I