



Endurance® Series

Accessories

Electrical Accessories

Multi-conductor cables* with M16 connector

The 12-wire cables are used for wiring the Endurance sensors with the 24 VDC power supply, all inputs, outputs, and the RS485 interface. A terminal strip is not included.

High temperature cable:	E-2CCB4	4 m (13 ft.)	Ambient temperatures:
	E-2CCB8	8 m (26 ft.)	UL-rated at -80 °C to 200 °C
	E-2CCB15	15 m (50 ft.)	(-112 °F to 390 °F)
	E-2CCB30	30 m (100 ft.)	Material:
	E-2CCB60	60 m (200 ft.)	cable is Teflon coated
Low-temperature cable	E-2CLTCB4	4 m (13ft.)	Ambient temperatures:
	E-2CLTCB8	8 m (26 ft.)	-40 °C to 85 °C (-40 °F to 185 °F)
	E-2CLTCB15	15 m (50 ft.)	Material:
	E-2CLTCB30	30 m (100 ft.)	cable is PUR–11Y (Polyurethane)
	E-2CLTCB60	60 m (200 ft.)	coated (Halogen free, Silicon free)

Note: Power supply maximum distance 60 m (200') from unit

Ethernet cables with M12, RJ45 connector for access to PoE, Ethernet

	E-ETHCB	7.5 m (25 ft.)	Ambient temperatures:
	E-ETHCB10	10 m (33 ft.)	-80 °C to 180 °C (-112 °F to 356 °F)
			Material:
			cable is Teflon coated.
	E-ETHLTCB	7.5 m (25 ft.)	Ambient temperatures:
	E-ETHLTCB25	25 m (80 ft.)	-40 °C to 80 °C (-40 °F to 176 °F)
	E-ETHLTCB50	50 m (160 ft.)	Material:
,			cable is PUR (Polyurethane) coated

Fiber-optic cables (for fiber-optic sensors only)

The fiber-optic cable is a sealed, stainless-steel armor sheath covering the fiber optic bundle. It withstands ambient temperatures up to 200 $^{\circ}$ C (390 $^{\circ}$ F), optional up to 315 $^{\circ}$ C (599 $^{\circ}$ F).

	EF1R and EF1M	models	EF2R and EF2M 1	nodels
Low temperature	O1BL	1 m (3 ft.)	O1BL	1 m (3 ft.)
	03BL	3 m (10 ft.)	O3BL	3 m (10 ft.)
	06BL	6 m (20 ft.)	06BL	6 m (20 ft.)
	10BL	10 m (33 ft.)	10BL	10 m (33 ft.)
	22BL	22 m (72 ft.)		
High temperature	O1BH	1 m (3 ft.)	O1BH	1 m (3 ft.)
	O3BH	3 m (10 ft.)	O3BH	3 m (10 ft.)
	06BH	6 m (20 ft.)	O6BH	6 m (20 ft.)
	10BH	10 m (33 ft.)	10BH	10 m (33 ft.)
	22BH	22 m (72 ft.)		

^{*} Not available with EF2ML and EF2RL

^{*} Cable doesn't include a terminal block. Please order E-TB or E-TBN4, if you want to include a terminal block.

Spare Parts (for fiber-optic sensors only)



EF1R Spare optical heads and fiber-optic cable assemblies

EF1R Spare optical heads		ls	(Focus options)
EF1RL-F2	EF1RM-F2	EF1RH-F2	sensor head with F2 (Standard Focus) focused at infinity (∞)
EF1RL-F0	EF1RM-F0	EF1RH-FO	sensor head with FO (Narrow Focus) focused at 100 mm (4")
EF1RL-F1	EF1RM-F1	EF1RH-F1	sensor head with F1 (Close Focus) focused at 300 mm (12")

EF1R Spare fiber-optic cables (non-laser only)

Low-temperature cables	High-temperature cables	Length
EF1RCB1BL	EF1RCB1BH	1 m (3 ft.)
EF1RCB3BL	EF1RCB3BH	3 m (10 ft.)
EF1RCB6BL	EF1RCB6BH	6 m (20 ft.)
EF1RCB1OBL	EF1RCB10BH	10 m (33 ft.)
EF1RCB22BL	EF1RCB22BH	22 m (72 ft.)

EF2R Spare optical heads and fiber-optic cable assemblies

EF2R Spare optical heads		(Focus options)
EF2RL-F2	EF2RH-F2	sensor head with F2 (Standard Focus) focused at infinity (∞)
EF2RL-F0	EF2RH-F0	sensor head with FO (Narrow Focus) focused at 100 mm (4")
EF2RL-F1	EF2RH-F1	sensor head with F1 (Close Focus) focused at 300 mm (12")

EF2R Spare fiber-optic cables (non-laser only)

EF2RL Low-temperature cables	EF2RL High-temperature cables	Length
EF2RLCB1BL	EF2RLCB1BHH	1 m (3 ft.)
EF2RLCB3BL	EF2RLCB3BH	3 m (10 ft.)
EF2RLCB6BL	EF2RLCB6BH	6 m (20 ft.)
EF2RLCB10BL	EF2RLCB10BH	10 m (33 ft.)

EF2RH	EF2RH	Length
Low-temperature cables	High-temperature cables	
EF2RHCB1BL	EF2RHCB1BH	1 m (3 ft.)
EF2RHCB3BL	EF2RHCB3BH	3 m (10 ft.)
EF2RHCB6BL	EF2RHCB6BH	6 m (20 ft.)
EF2RHCB1OBL	EF2RHCB10BH	10 m (33 ft.)

(Electrical accessories)

(Electrical accessories)	1	
	E-TB	Endurance terminal block accessory for connecting the Endurance sensor with the customer's industrial environment
	E-TBN4	Endurance terminal block in an IP65 (NEMA 4) enclosure with sealed cable inlets The inside the enclosure installed terminal block is equal to the above-described E-TB type.
	E-SYSPS	Industrial power supply, DIN rail mount delivers isolated dc power and provides short circuit and overload protection Protection class prepared for class II equipment Environmental protection IP20 Operating temperature -25 °C to 55 °C (-13 °F to 131 °F) AC input 100 - 240 VAC, 44 - 66 Hz DC output 24 VDC / 1.3 A
	E-PS	Power supply & Endurance terminal block mounted in an IP65 (NEMA 4) enclosure AC input 100 - 240 VAC, 50 - 60 Hz DC output 24 VDC / 1.1 A Ambient temperatures 0 °C to 50 °C (32 °C to 120 °F) Humidity 20 to 90%, non-condensing
	E-POE	PoE Injector provides power and also acts as a single Ethernet hub. AC input 100 – 240 VAC, 50 – 60 Hz PoE power up to 15.4 W PoE output ports 1 RJ-45 10/100/1000 Mbps Standards IEEE 802.3, IEEE 802.3u, IEEE 802.3af (PoE standard)
	E-2CCON	12-socket DIN Cable connector for multi-conductor cable
	E-M5PK	Ircon® Modline® 5 patch cable kit allows Endurance use with existing Modline 5 cables.
	E-M5PKMC	Endurance patch cable kit allows Modline 5 use with existing Endurance cables
	E-USB485	USB to RS232/422/485 converter for the direct adaptation of an Endurance series device to a standard PC via the USB-interface



E-CP

Cooling platform for electronics housing

can be used for ambient temperatures up to 150 °C (302 °F)

Mechanical/Optical	Accessories f	or Integrated Sensors only
3	E-AP	Air purge collar to keep dust, moisture, airborne particles and vapors away from the lens
	E-PA	Pipe adapter to adapt a 300 mm (12") sighting tube to the Endurance device
	E-MN	Mounting nut (spare) to fix and secure the Endurance device to any kind of mounting brackets (inner thread of 36.9 mm (1.5") UNC)
9	E-FB	Fixed bracket (spare) to mount the Endurance sensor in a fixed location (swivel range of about 45°)
	E-AB	Adjustable bracket to mount the Endurance sensor in a moveable position. It allows pitch and swivel of the sensor-sighting axis in a range of approximately 45° per axis
	E-SB	Swivel bracket to mount the Endurance sensor in a moveable position. It allows pitch $(0^{\circ} - 45^{\circ})$ and swivel $(0^{\circ} - 360^{\circ})$ of the sensor-sighting axis
	E-RA	Right angle mirror for targets at right angles to sensor axis The right angle mirror has an air-purge adapter.
	E-M5WJAK	Modline 5 WaterJacket (WJA) adapter kit is required to modify the WJA to allow the Endurance sensor to be secured in the Modline 5 WJA.
	E-UAA	Endurance universal adapter accessory clamps around the Endurance sensor and can be used to mount it to an existing Modline 5 installation, where a RAM (Right Angle Mount) is used, a tripod, or any device using a 1/4–20 UNC threaded mounting hardware
7	E-AK-7	Adapter kit for mounting Endurance into existing WJ-5 water jacket installations



(Mechanical/Optical Accessories for Integrated Sensors only)

	E-MF-7	Mounting flange allows an Endurance sensor to be mounted into an existing Ircon flange mount installation This accessory needs to be used in conjuction with the E-MFA-7 flange adapter.
	E-MFA-7	Flange adapter to allow Endurance sensor to mount to MF-7 mounting flange
	E-PC	Protection cap kit for Endurance sensor M12 and M16 sockets
	E-ECAP	Replacement glass end-cap is the replacement of a defect or damaged Endurance end cap
0	E- PW	Protective front window, including O-Ring The protective front window with the needed O-ring is orderable as a spare part.
	E-PFEC	Polarizing filter end cap The filter protects the eyes when sighting on bright, high temperature targets through the visual sighting port. The filter does not affect measured energy. The polarizing filter will not fit in the standard end cap.

Mechanical/Optical Accessories for Fiber-optic Sensors only			
1000	E-FOMB	Adjustable mounting bracket to mount the Endurance fiber-optic head (incl. 2 mounting nuts)	
De.	Е-ГОНАРА	Air purge collar to keep dust, moisture, airborne particles, and vapors away from the optical head's lens It includes a stainless steel sighting-tube that threads onto the front of the air purge collar.	

(Mechanical/Optical Accessories for Fiber-optic Sensors only)

	Fitting System Flexible accessory selections allow you to pick and choose the accessories you need		
	E-FORFQP	Stainless steel air purge with quick release fitting and sapphire window air connector (1/4" NPT)	
	E-FORFAP	Stainless steel air purge with quick release fitting, sapphire window (E-FORFQP) and stainless steel tube (203 mm/8 in)	
	E-FORFMF	Stainless steel air purge with quick release fitting, sapphire window (E-FORFQP) and stainless steel 4-bolt mounting flange	
	E-FORFMC	Stainless steel air purge with quick release fitting, sapphire window (E-FORFQP) and stainless steel gravity-held mounting base	
	E-BF1WINDOW	Sapphire protective window mounted in stainless steel bezel	
	Е-ГОХНЗ	High temperature fiber-optic housing with air-knife purge and sapphire protective window 3 m (10 ft.) air/protection hose, for extreme environments with ambient temperature <= 450 °C (842 °F)	
	Е-ГОХН6	High temperature fiber-optic housing with air-knife purge and sapphire protective window 6 m (20 ft.) air/protection hose, for extreme environments with ambient temperature <= 450 °C (842 °F)	



ThermoJacket and R	elated Acce	ssories
	E-TJ1M	ThermoJacket housing to use Endurance series sensing heads in ambient temperatures up to 315 °C (600 °F) The ThermoJacket provides water and/or air-cooling and air purging in one unit. Ambient temperatures: water cooling 315 °C (600 °F) air cooling 115 °C (240 °F)
	E-MF	Mounting flange for ThermoJacket to mount the ThermoJacket to walls, existing ports or flanges.
.0	E-MB	Adjustable mounting base for ThermoJacket provides stable, permanent placement of the ThermoJacket while allowing the ThermoJacket to swivel 360° and pitch 90° forward.
	E-GTQ	Blast gate assembly with quartz window (HT model) to protect the sensor, and perform tasks without exposure to hot or explosive target areas. Specification: max. 870 °C (1600 °F)
H-MC	E-APA	Adjustable pipe adapter assembly can be placed permanently on a surface and aimed in any direction within a 45° radius
	E-MST	Mounting flange for use with sighting tubes to adapt different kind of sighting tubes to the Endurance sensor in ThermoJacket installation
	E-STC12	30 cm (12") sighting tube, ceramic Use the E-STC12 ceramic sighting tube in conjunction with the E-MST tube-mounting flange in temperature measurement environments where reflected energy is a problem Specification: up to 1500 °C (2730 °F)
	E-ST12	30 cm (12") sighting tube, stainless steel Use the E-ST12 stainless steel sighting tube in conjunction with the E-MST tube-mounting flange in temperature measurement environments where reflected energy is a problem Specification: up to 800 °C (1470 °F)



(ThermoJacket and Related Accessories)

E-BEESIGHT	30 cm (12") sighting tube, carbon steel with 45 degree end cut and slotted weep hole at base. Use the E-BEESIGHT carbon steel sighting tube in conjunction with the E-MST tube-mounting flange in temperature measurement environments where reflected energy is a problem. Specification: up to 800 °C (1470 °F)
E-TJET	Extraction tool eases the removal of an Endurance sensor from the ThermoJacket protective enclosure

Flow Regulator Access	sories (for use	with cooling/purging options)
	E-AR	Air purging flow regulator assembly with air filter to control air purging
A Company of the Comp	E-CAFR	Cooling air flow regulator (high capacity) to control air-cooling in high ambient temperature environments
A service of the serv	E-WR	Water flow regulator to control water-cooling



Line Scanning Accessory

SSA



SpotScan[™]

When mounted to the front of the Endurance sensor, the SpotScan accessory allows the user to gather temperature information over a larger area on the target, due to the scanning mechanism inside the accessory.

Scan angle 2 - 15° Scan Frequency 0.5 - 5 Hz

Operating Temperature 0 °C - 60 °C (32 °F - 140 °F)

18 - 32 VDC, 12W Power Supply **Enclosure Rating** IP65 (when sensor is

fitted in accessory)

Window material N-BK7

The Fluke Process Instruments Guarantee

The Endurance Series is supported by a 4 year warranty. With a network of trained representatives and agents in over one hundred (100) countries and offices located in the U.S., Germany and China, we provide local service and support you can rely on time after time.

Fluke Process Instruments

Americas

Santa Cruz, CA USA

+1 800 227 8074 (USA and Canada, only)

+1 831 458 3900

solutions@flukeprocessinstruments.com

EMEA

Berlin, Germany Tel: +49 30 4 78 00 80 info@flukeprocessinstruments.de

Beijing, China

+8610 6438 4691

info@flukeprocessinstruments.cn

Tokyo, Japan

+81 03 6714 3114

info@flukeprocessinstruments.jp

Asia East and South

India Tel: ++91 22 2920 7691 Singapore Tel: +65 6799 5578 sales.asia@flukeprocessinstruments.com

Worldwide Service

Fluke Process Instruments offers services, including repair and calibration. For more information, contact your local office.

www.flukeprocessinstruments.com

© 2017 Fluke Process Instruments Specifications subject to change without notice. 09/2017 ED_Access_DS_RevC